



...the future

6W EMERGENCY LIGHT

-Injection- molded ABS plastic housing

-Innovative, easy installation in minutes

-Test switch/LED charge indicator provided

-Suitable for damp locations

-Safe to be used in Food and Beverage Manufacturing facilitates

Rated voltage: 100-277V, 60Hz

Rated power: 6W

Emergency time: 3hrs

Emergency power: 6W

Emergency switch time: ≤0.25s

Emergency output flux: ≥50lm

Lamp: 2x6 pieces SMD 5050 LED Lamps for emergency

Battery: Replaceable lead acid battery

Charging time: ≤24h

Ingress protection: IP20